

ANTREX Electronics

Electronic Components Sourcing Information

Product Reference Information

Part Number:	LVR008S-1
Manufacturer:	Littelfuse Inc.
Package:	Radial, Disc
Availability:	Please confirm with sales

Product Page:

<https://antrexco.com/product/details/littelfuse-inc/lvr008s-1.html>

Request a Quote:

[Submit RFQ for this part](#)



Scan for product page

Contact Information

Email: info@antrexco.com

WhatsApp: +86-186-8066-5326

Website: <https://antrexco.com>

Quality & Trust

New & Original Components

Supplier verification and packaging condition review

CoC / RoHS / REACH documents available on request

Secure sourcing support for OEM / EMS projects

Note:

This PDF includes an ANTREX product reference cover page.

The original manufacturer datasheet follows from the next page.

Tyco/Electronics
Raychem Circuit Protection
 308 Constitution Drive
 Menlo Park, CA 94025-1164
 800-227-4856
 FAX 800-227-4866

PolySwitch®
PTC Devices
 Overcurrent Protection Device

PRODUCT: LVR008S

DOCUMENT: SCD 24903
 PCN: 029390
 REV LETTER: H
 REV DATE: JUNE 18, 2003
 PAGE NO.: 1 OF 2

Specification Status: RELEASED

Electrical Rating at 20°C

Rated Operating Voltage: 240 V_{AC}

Rated Interrupt Current: 1.2 A_{RMS}

Max Interrupt Voltage: 265 V_{AC}

Insulating Material :
 Cured, Flame Retardant Epoxy Polymer
 Meets UL94 V-0 Requirements.

Lead Material: 24 AWG Sn Plated Copper

Marking:

Raychem Logo
 and Voltage
 X 240

L008 Part Identification

Lot Identification
 (can be on back)




TABLE I. DIMENSIONS:

	A		B		C		D		E	
	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX
mm:	--	8.3	--	10.7	4.3	5.8	7.6	--	--	3.8
in*:	--	(0.33)	--	(0.43)	(0.17)	(0.23)	(0.30)	--	--	(0.15)

*Rounded off approximation

TABLE II. PERFORMANCE RATINGS:

I _{HOLD} RATED CURRENT	CURRENT RATINGS		TIME TO TRIP	RESISTANCE		POST-TRIP RESISTANCE STANDARD TRIP	NOMINAL TRIPPED POWER DISSIPATION
AMPS AT 20°C HOLD	AMPS AT 20°C		SECONDS AT 20°C, 0.4A MAX	OHMS AT 20°C		OHMS AT 20°C MAX	WATTS AT 20°C
	HOLD	TRIP		MIN	MAX		
0.08	0.08	0.19	15.0	7.4	12.0	26.0	0.8

Recognitions:

Reference Documents:

Precedence:

Effectivity:

Warning:

UL, TUV, CSA recognized.

PS300

This specification takes precedence over documents referenced herein.

Reference documents shall be the issue in effect on the date of invitation for bid.

Refer to Page 2 of this document for application limitations.

Tyco/Electronics
Raychem Circuit Protection
308 Constitution Drive
Menlo Park, CA 94025-1164
800-227-4856
FAX 800-227-4866

PolySwitch®
PTC Devices
Overcurrent Protection Device

PRODUCT: LVR008S

DOCUMENT: SCD 24903
PCN: 029390
REV LETTER: H
REV DATE: JUNE 18, 2003
PAGE NO.: 2 OF 2



WARNING

Warning: Application Limitations for LVR Product Line

1. Users should independently evaluate the suitability of and test each product selected for their own application.
2. This product should not be used in an application where maximum interrupt voltage or maximum interrupt current can be exceeded in a fault condition. Operation beyond the maximum ratings or improper use may result in device damage and possible electrical arcing and flame.
3. A PTC device is not a fuse - it is a nonlinear thermistor that limits current. Because under a fault condition all PTC devices go into a high resistance state but not open circuit, hazardous voltage may be present at PTC locations.
4. The devices are intended for protection against occasional overcurrent or overtemperature fault conditions and should not be used when repeated fault conditions or prolonged trip events are anticipated.
5. In most applications, power must be removed and the fault condition cleared in order to reset a PTC device. However, under certain unusual conditions, a PTC device may automatically reset (see Raychem Circuit Protection Databook). Accordingly, PTC devices should not be used in an application where an automatic reset could create a safety hazard, such as garbage disposals and blenders.
6. It is the responsibility of the user to determine the need for back up or fail safe protection to prevent damage that may occur in the event of abnormal function or failure of the PTC device.
7. Operation in circuits with a large inductance can generate a circuit voltage ($L di/dt$) above the rated voltage of a PTC device.
8. Devices are not recommended for reflow soldering.
9. Device performance can be impacted negatively if devices are handled in a manner inconsistent with recommended electronic, thermal, or mechanical procedures for electronic components.
10. PTC devices are not recommended to be installed in applications where the device is constrained such that its PTC properties are inhibited, for example in rigid potting materials or in rigid housings which lack adequate clearance to accommodate device expansion.
11. Contamination of the PTC material with certain silicone-based oils or some aggressive solvents can adversely impact the performance of the devices.